

SBR Shoe Box Retrofit Kit



Product Description

The Shoe Box Retrofit Kit with Lumen-Starr T12 LED lamp tubes. LED diodes are recessed into an aluminum housing creating cooler operation, longer lamp life and higher lumen output. Lamps are 180 degree rotational allowing for all needed types of lamp distribution.

Features & Benefits

- *LED lamp distribution meets "Dark Sky" requirements.
- *Direct retrofit: Remove HID components and reflector, install driver tray assembly, wire to power, install LED lamps, ready to light.

Performance Summary

- *LED Diodes are 2W @ 114lm/w (initial)
- *Average rated life (hr): >50,000
- *Diameter: 1-1/2"
- *Base: Medium Bipin
- *CRI: WW=85
CW=80
- *CCT: 3500K & 4100K
- *LM-79 & LM-80

Power Supply

- *Class 2 Driver (Power Factor>99%, THD<10%)
- *Operating Voltage: 120/277V
- *Output current: 750Ma max.


Ordering Information

- SBR 409-36** - 2ft w/ 4-T12 lamp tube, 72W, 8,208lm (initial)
- SBR 609-54** - 2ft w/ 6-T12 lamp tube, 108W, 12,312lm (initial)
- SBR 809-72** - 2ft w/ 8-T12 lamp tube, 144W, 16,416lm (initial)
- SBR 109-90** - 2ft w/10-T12 lamp tube, 180W, 20,520lm (initial)

Lamp/Driver Information

- LED9T12RWW** - 2ft Linear lamp tube with 9 LEDs, 18W, 3500K, 2,052lm (initial)
- LED9T12RCW** - 2ft Linear lamp tube with 9 LEDs, 18W, 4100K, 2,052lm (initial)

LED11618-UNV-DR - Driver, 16-18 LEDs, 120/277V



Outdoor Applications



T12 Linear Lamp Tube

Patent No. US 7,635,201 B2

